

FireProtect 2  
Heat/Smoke

# FireProtect 2 Heat/Smoke

Wireless smoke and heat detector



---

## Compatibility

### Hubs

Hub Plus

Hub 2 (2G)

Hub 2 (4G)

Hub 2 Plus

Hub Hybrid (2G)

Hub Hybrid (4G)

### Radio signal range extenders

ReX

## ReX 2

---

# Communication

## Jeweller communication technology

Proprietary wireless technology for transmission of alarms and events.

Features:

- Two-way communication.
- Protection against device spoofing.
- Block encryption featuring a floating key.
- Instant notifications.
- Remote configuration via the Ajax apps.

[Learn more](#)

## Frequency bands

866.0 – 866.5 MHz

868.0 – 868.6 MHz

868.7 – 869.2 MHz

905.0 – 926.5 MHz

915.85 – 926.5 MHz

921.0 – 922.0 MHz

Depends on the sales region.

## Maximum effective radiated power (ERP)

up to 20 mW

Automatic power control to reduce power consumption and radio interference.

## Radio signal modulation

GFSK

## Radio communication range

up to 1,700 m

Between the detector and a hub (or radio signal range extender) in an open space.

**Calculate radio communication range**

## Encryption of radio communication

All the data stored and transmitted are protected by block encryption with a floating key.

## Radio frequency hopping

To prevent radio interference and jamming.

**Learn more**

---

## Sensitive elements

smoke sensor

temperature sensor

---

## Smoke detection

### Sensitive element

double-spectrum optical sensor

Recognizes smoke by the size of particles in the air.

### Protection from false alarms

Does not react to water vapour.

### Patented smoke chamber



Protects the smoke sensor from dust, dirt, and insects.

---

## Dangerous temperature detection

### Sensitive element

according to the requirements for Class A1 temperature detectors

Requirements of EN 54-5 and BS 5446-2 standards.

### High temperature alarm

at temperatures above 64°C

### Temperature spike alarm

when the temperature rises more than 10°C in 1 minute or less

---

## Additional features

### In-built siren

volume 85 dB at a distance of 3 meters

Sound notification of alarms. Active until the reason for triggering is eliminated or until the user disables notification.



### Interconnected Fire Detectors Alarms

All fire detectors in the system turn on built-in sirens if at least one of the detectors registers an alarm. An interconnected fire alarm is activated during one “hub – detector” polling interval but no more than 20 seconds later.

**Learn more**



## LED indication

green is a power indication

A LED indicator on the device enclosure lights up once every 56 seconds. The indication meets the requirements of EN 50291.

yellow is an indication of malfunctions

A LED indicator on the device enclosure lights up when malfunctions are detected. For example, in the case of discharged batteries, contamination of the smoke chamber, or end of the service life.

red is an indication of fire alarms

A LED indicator on the device enclosure lights up when the detector registers a fire alarm.



## Button on the front panel of the detector

In normal mode, when pressed, it starts the smoke chamber test. In the event of an alarm or malfunction, the pressing turns off the detector sound notification.



## Recommendations

The device is designed only for indoor installation.

SmartBracket mounting panel allows adjusting the position of the detector after installation.

---

## Anti-sabotage protection

### Tampering alarm

Alerts of attempts to detach the detector from the surface or remove the mounting panel.

[Learn more](#)

### Protection against spoofing

device authentication

### Detection of communication failure

within 15 minutes

The time to detect communication loss depends on the settings for the number of undelivered data packages (specified in the **Jeweller** or **Jeweller/Fibra** settings). The polling interval is fixed at 300 seconds

[Learn more](#)

---

## Power supply

### For FireProtect 2 RB (Heat/Smoke)

2 × CR123A battery

Up to 7 years of battery life.

### For FireProtect 2 SB (Heat/Smoke)

2 non-replaceable lithium batteries

Up to 10 years of battery life.

---

## Enclosure

### Dimensions

123,7 × 123,7 × 44,7 mm

### Weight

272,5 g

For FireProtect 2 RB (Heat/Smoke).

TBC g

For FireProtect 2 SB (Heat/Smoke).

### Operating temperature range

from 0°C to +50°C

### Operating humidity

up to 80%

### Protection class

IP20



---

## Colours

**Black**

**White**



---

## Complete set

### For FireProtect 2 RB (Heat/Smoke)

FireProtect 2 RB (Heat/Smoke) Jeweller  
SmartBracket mounting panel  
2 × CR123A battery (pre-installed)  
Installation kit  
Quick Start Guide

### For FireProtect 2 SB (Heat/Smoke)

FireProtect 2 SB (Heat/Smoke) Jeweller  
SmartBracket mounting panel  
Installation kit  
Quick Start Guide

## Additional information

### Compliance with standards

[Learn more](#)

### Warranty

24 months

[Learn more](#)




## Subscribe

Subscribe to our emails about secure life. No spam.

## Software





## Company

- [About](#)
- [Why Ajax](#)
- [Support](#)
- [How it works](#)
- [For partners](#)
- [Blog](#)
- [Events](#)
- [Press page](#)
- [Careers](#)

## Products

- [All products](#)
- [Scenarios](#)
- [Build your system](#)
- [Reviews](#)
- [Suggested features](#)
- [CMS connection](#)
- [Enterprise API](#)
- [Compliance with standards](#)

## Request extra help

-  [support@ajax.systems](mailto:support@ajax.systems)
-  [@AjaxSystemsSupport\\_Bot](#)

[Privacy policy](#) [Anti-Spam Policy](#) [End user agreement](#) [Warranty](#)

© 2022 AJAX SYSTEMS CH. All rights reserved