

### ပုံစံ (၁) - မြန်မာနိုင်ငံတော် အစိုးရအဖွဲ့၏ အမိန့် (၂၀၁၅) ခုနှစ်၊ ဇူလိုင်လ ၁၁ ရက်နေ့၊ ပူးတွဲချက် (၁) ဖြစ်ပါသည်။

- ၁။ ကိုယ်စားပြုအဖွဲ့ဝင်
- ၂။ စာရင်းအုပ်စုအဖွဲ့ဝင်
- ၃။ အထူးအရေးယူမှုအဖွဲ့ဝင်များအဖွဲ့ဝင်
- ၄။ မြန်မာ့စွယ်စုံကျမ်းရေးရာအဖွဲ့ဝင်များအဖွဲ့ဝင်
- ၅။ မြန်မာ့စွယ်စုံကျမ်းရေးရာအဖွဲ့ဝင်များအဖွဲ့ဝင်
- ၆။ မြန်မာ့စွယ်စုံကျမ်းရေးရာအဖွဲ့ဝင်များအဖွဲ့ဝင်
- ၇။ မြန်မာ့စွယ်စုံကျမ်းရေးရာအဖွဲ့ဝင်များအဖွဲ့ဝင်
- ၈။ မြန်မာ့စွယ်စုံကျမ်းရေးရာအဖွဲ့ဝင်များအဖွဲ့ဝင်
- ၉။ မြန်မာ့စွယ်စုံကျမ်းရေးရာအဖွဲ့ဝင်များအဖွဲ့ဝင်
- ၁၀။ မြန်မာ့စွယ်စုံကျမ်းရေးရာအဖွဲ့ဝင်များအဖွဲ့ဝင်

# AVerMedia

## AVerDiGi SA6000E/6032E/9416 RACK Series Hybrid Standalone NVR



**New**  
**Built-in e-SATA connector**  
 e-SATA connector enables DVR to connect with external SATA interface storage devices, and have more capacity to save video.



**New**  
**Built-in RS485 connector**  
 With built-in RS485 connector, DVR can immediately integrate with RS485 interface peripheral such as PTZ, POS, and more.



**Hybrid NVR**  
 Support MegaPixel, IP and Analog PTZ/cameras of most popular brands such as AXIS, SONY, Panasonic, Arecont and more.



**Hybrid TV out & Spot monitor**  
 Provide multiple IP and Analog channels display on CCTV monitor and pop up the channel once alarm triggered.




**Hybrid Dual monitor**  
 Support IP and Analog dual monitor environment for independent preview and playback or E-map to save your trouble switching.



**AVerDiGi FaceFinder**  
 AVerDiGi FaceFinder enables DVR to detect human face in live video and trigger instant playback from object index.

### AVerDiGi SA6000E/SA6032E/9416 RACK Series + AVerDiGi Display 21

AVerDiGi SA6000E/SA6032E/9416 RACK Series only support up to 2 multi-quad outputs. After combining with Display 21, they will be enhanced to support up to **12 multi-quad outputs and 32 loop-through TV outputs**. Managers can efficiently monitor every corner as they want and have more flexible usage with Display 21 for various security purposes.



▶ Multi-Quad 6 different Display Modes



# Application



IP PTZ



PTZ



Analog Camera



IP Camera (up to MegaPixel)

## Camera Integration

Suitable for different environment to use



### System Integration

Easy for retailers and enterprise to use and control.



AVerDIGI POS box POS ATM

### Com Port Expansion Device

Com port expansion card or box can support external com port devices up to 16

### System Controller



### Security System

Multiple launch programs to protect your assets.



Printer Light Telephone



Alarm LCD TV



AVerDIGI Access Control Home Appliance SMS / MMS



E-Mail Microphone Sensor



### Backup Device

Various backup devices supported for every project's demand.



CD / DVD-RW External HDD Disk Array



Pen Drive NAS AVerDIGI RA4000e



AVerDIGI SA6000E/SA6032E/9416 RACK Series



## Remote Monitoring



### Central Management

Security guard can monitor and remote control DVR via CM3000 for instant notification

#### CM3000



### 2-Way Audio

For instant mutual communication regardless of distance



### Remote Access

Enable users to monitor any time and everywhere via



WebViewer



PDAViewer



HandyViewer / SmartViewer (for Symbian/Windows smart phone)



Remote Console



### Software Development Kit

Users can integrate our system through 3rd party's intelligent software to customize their function, such as


- Customized UI
- ATM system
- Facial Recognition
- License Plate Recognition
- .....and more to meet your need

## Product Specifications

	SA6000E RACK		SA6032E RACK		SA9416 RACK	
Model	SA6416E RACK	SA6416E RACK+Display 21	SA6832E RACK	SA6832E RACK+Display21	SA9416 RACK	SA9416 RACK+Display21
Operating system	Embedded OS					
Compression	S/W compression				H/W compression	
Video format	MPEG4/H.264				MPEG4	
Video input	16		32		16	
Video loop output	N/A	16	N/A	32	N/A	16
Multiple-quad output	1	6	2	12	1	6
Display rate (NTSC/PAL)	480/400 fps		960/800 fps		480/400 fps	
Recording frame rate (CIF)	480/400 fps		960/800 fps		480/400 fps	
Recording frame rate (VGA)	240/200 fps		960/800 fps		N/A	
Recording frame rate (D1)	160/128 fps		320/256 fps		480/400 fps	
Audio input	16		32		16	
Sensor/Relay	4/4		8/8	4/4	4/4	
DVD-RW	Yes					
Removable HDD tray	1 HDD tray (support up to 4 HDDs)		1 HDD tray (support up to 6 HDDs)		1 HDD tray (support up to 4HDDs)	
DOM	2G DOM					
HDD	500GB					
H/W accessory	AverDiGi MU3000 (Mouse)					
Ethernet	RJ-45, 10/100/1000 Mbps					
RS232 (com port)	1		N/A			
RS485	1					
e-SATA port	1					
USB 2.0	Front 2 ports, Rear 4 ports		Front 2 ports, Rear 6 ports		Front 2 ports, Rear 4 ports	
LCD Display	N/A					
Operation via front panel	N/A					
Dimensions (W x H x D)	482 x 133 x 529 mm					
Power	350 Watt					
Dual-monitor output	Yes					

Specifications are subject to change without prior notice

## Product Illustration



The product illustration is based on SA6832E RACK+Display 21 model



All right reserved. No part of this document may be reproduced, stored in a retrieval system, or transmitted in any form or by any means (Electronic, mechanical, photocopy, recording, or otherwise) without the written permission of AVerMedia INFORMATION, Inc. Information in this document is subject to change without notice. The information contained herein, is to be considered for informational purposes only and shall not be considered legally binding. 2008 by AVerMedia INFORMATION, Inc. All rights reserved. No part of this publication may be reproduced, transmitted, transcribed, stored in a retrieval system, or translated into any language in any form by any means without the written permission of AVerMedia INFORMATION, Inc. AVerMedia is registered trademarks of AVerMedia INFORMATION, Inc. All other trademarks belong to their respective companies. Made in Taiwan. 20081206

**AVerMedia**<sup>®</sup>  
[www.avermedia.com](http://www.avermedia.com)  
[www.averdigi.com](http://www.averdigi.com)